

| 型号 | | M8871 | M8872 | M8873 | M8874 |
|--------|--|---------------|---------------|---------------|---------------|
| 额定输出 | 电压 | 0-15V | 0-30V | 0-75V | 0-100V |
| | 电流 | 0-60A | 0-35A | 0-15A | 0-11A |
| 负载调节率 | 电压 | < 0.01%+1mV | < 0.01%+1mV | < 0.01%+1mV | < 0.01%+1mV |
| | 电流 | < 0.01%+0.1mA | < 0.01%+0.1mA | < 0.01%+0.1mA | < 0.01%+0.1mA |
| 设定值分辨率 | 电压 | 0.1mV | 0.5mV | 2mV | 2mV |
| | 电流 | 1mA | 0.5mA | 0.2mA | 0.2mA |
| 回读值分辨率 | 电压 | 0.1mV | 0.1mV | 0.1mV | 1mV |
| | 电流 | 0.1mA | 0.1mA | 0.1mA | 0.1mA |
| 设定值精度 | 电压 | 0.01%+1mV | 0.01%+5mV | 0.01%+10mV | 0.01%+15mV |
| | 电流 | 0.05%+6mA | 0.05%+2mA | 0.05%+1mA | 0.05%+1mA |
| 回读值精度 | 电压 | 0.03%+3mV | 0.03%+5mV | 0.03%+15mV | 0.03%+25mV |
| | 电流 | 0.05%+45mA | 0.05%+25mA | 0.05%+12mA | 0.05%+10mA |
| 纹波 | 电压 | 4mvp-p | 5mvp-p | 6mvp-p | 8mvp-p |
| | 电流 | 15mA rms | 8mA rms | 3mA rms | 2.5mA rms |
| 电压表精度 | 0-12V 精度: 0.02%+2mV 0-58V 精度: 0.02%+5mV | | | | |
| 毫欧姆表精度 | 10W. 0-1000mΩ 精度: 0.2%+3mΩ 1000-10000 mΩ 精度: 0.2%+6mΩ | | | | |
| 工作环境 | 0-40°C; 0-90%RH | | | | |
| 使用电源 | AC 125V/220V ₋ +10%; 50/60HZ | | | | |
| 重量 | 45Kg | | | | |
| 机架安装尺寸 | 482mmW×184.5mmH×531mmD | | | | |